

Issued by	NMi Certin B.V., designated and notified by the Netherlands to perform tasks with respect to conformity modules mentioned in article 17 of Directive 2014/32/EU, after having established that the Measuring instrument meets the applicable requirements of Directive 2014/32/EU, to:
Manufacturer	Kanlux S.A. ul. Objazdowa 1-3 41-922 Radzionków Poland
Measuring instrument	A static Active Electrical Energy Meter Type : KDEM-3P LCD Manufacturer's mark or name : Kanlux Reference voltage : 3x230/400 V Reference current : 10 A Destined for the measurement of : electrical energy, in a - three-phase four-wire network Accuracy class : B Environment classes : M1 / E2 Temperature range : -25 °C / +55 °C Further properties are described in the annexes: - Description T11332 revision 0; - Documentation folder T11332-1.
Valid until	2 May 2028

Issuing Authority **NMi Certin B.V., Notified Body number 0122**
2 May 2018



C. Oosterman
Head Certification Board

NMi Certin B.V.
Hugo de Grootplein 1
3314 EG Dordrecht
The Netherlands
T +31 78 6332332
certin@nmi.nl
www.nmi.nl

This document is issued under the provision that no liability is accepted and that the manufacturer shall indemnify third-party liability.

The designation of NMi Certin B.V. as Notified Body can be verified at <http://ec.europa.eu/enterprise/newapproach/nando/>

Reproduction of the complete document only is permitted.

1 General information about the instrument

All properties of the static active electrical energy meter, whether mentioned or not, shall not be in conflict with the legislation.

1.1 Essential parts

Description	Document	Remarks
measuring sensor	11332/0-03	
printed circuit board	11332/0-06 and 11332/0-07	

1.2 Essential characteristics

- 1.2.1 See EU-type examination certificate T11332 revision 0 and the characteristics mentioned below.
- 1.2.2 Approved meter types : KDEM-3P LCD
- 1.2.3 Frequency : 50 Hz
- 1.2.4 Meter constant : 400 imp./kWh
- 1.2.5 Number of registers : 1
- 1.2.6 Export energy : The meter is not capable of measuring energy in 2 directions.
- 1.2.7 Software specification (refer to WELMEC 7.2):
 - Software type P;
 - Risk Class C;
 - Extension L, D, S and T are not applicable.

FW version / checksum	Remarks
9bf7	The software version and checksum are displayed at start-up.

1.3 Essential shapes

- 1.3.1 The nameplate is bearing at least, good legible, the information as mentioned in the regulations on energy meters. An example of the markings is shown in document no. 11332/0-02.
- 1.3.2 Sealing: see chapter 2.
- 1.3.3 The registration observation is executed by means of an LED.

1.4 Conditional parts

1.4.1 Terminal block

The connections for the current cables on the terminal block have a diameter of at least 7 mm. The cables are connected with the terminal block via one screw. See document no.11332/0-04.

1.4.2 Housing

The meter has got a dustproof housing, which has sufficient tensile strength. The cover is made of synthetic material. An example of the housing is presented in document no. 11332/0-01.

1.4.3 Terminal cover

The terminal cover is made of synthetic material.

1.4.4 Register

The quantity of measured energy is presented by means of a display with at least 6 elements. For test purposes an indication with a least significant element of at least 0,01 kWh, is available.

1.5 Conditional characteristics

1.5.1 Maximum current:

smaller than or equal to 100 A, and at least 5 times higher than the reference current.

Terminal block:

Maximum current	Document no.	Remarks
100 A	11332/0-04	

1.5.2 Minimum current: 0,5 A

1.6 Non-essential parts

1.6.1 Pulse output

2 Seals

The meter is sealed with a wire seal.

An example of the sealing is presented in document no. 11332/0-05.

3 Conditions for conformity assessment according to module D or F

The influence factors for temperature, frequency and voltage, which are necessary to perform the conformity assessment according to module D or F, are presented in Annex 1, belonging to this EU-type examination certificate.

Based on the WELMEC 11.1, section 2.5.6, the sum of the square values is presented.

Influence factors for temperature, frequency and voltage

During the type approval examination the influence factors for temperature, frequency and voltage are determined per load point. The values depicted in the table below present the root sum square values per load point, determined via the following formula:

$$\delta e(T, U, f) = \sqrt{\delta e^2(T, I, \cos \varphi) + \delta e^2(U, I, \cos \varphi) + \delta e^2(f, I, \cos \varphi)}$$

with:

- $\delta e(T, I, \cos \varphi)$ = the additional percentage error due to the variation of the temperature at a certain load;
- $\delta e(U, I, \cos \varphi)$ = the additional percentage error due to the variation of the voltage at the same load;
- $\delta e(f, I, \cos \varphi)$ = the additional percentage error due to the variation of the frequency at the same load.

Current	Power factor	Error -25°C [%]	Error -10°C [%]	Error +5°C [%]	Error +23°C [%]	Error +40°C [%]	Error +55°C [%]
I _{min}	1	0.3	0.2	0.1	0.1	0.1	0.2
I _{tr}	1	0.3	0.2	0.2	0.1	0.1	0.2
	0,5 ind.	0.3	0.2	0.2	0.1	0.2	0.3
	0,8 cap.	0.2	0.2	0.1	0.1	0.1	0.2
I _{tr} phase R	1	0.2	0.1	0.1	0.1	0.1	0.2
	0,5 ind.	0.4	0.3	0.2	0.1	0.2	0.3
I _{tr} phase S	1	0.2	0.2	0.1	0.1	0.1	0.2
	0,5 ind.	0.2	0.2	0.2	0.2	0.2	0.2
I _{tr} phase T	1	0.4	0.3	0.2	0.1	0.1	0.3
	0,5 ind.	0.2	0.2	0.2	0.1	0.2	0.3
10 I _{tr}	1	0.3	0.2	0.1	0.1	0.1	0.2
	0,5 ind.	0.3	0.2	0.2	0.1	0.1	0.3
	0,8 cap.	0.3	0.2	0.1	0.0	0.1	0.2
10 I _{tr} phase R	1	0.2	0.2	0.2	0.2	0.2	0.2
	0,5 ind.	0.5	0.4	0.4	0.4	0.4	0.5
10 I _{tr} phase S	1	0.2	0.2	0.1	0.1	0.1	0.2
	0,5 ind.	0.2	0.2	0.3	0.2	0.2	0.3
10 I _{tr} phase T	1	0.4	0.3	0.2	0.1	0.2	0.3
	0,5 ind.	0.3	0.2	0.2	0.1	0.1	0.3
I _{max}	1	0.4	0.3	0.2	0.1	0.2	0.3
	0,5 ind.	0.4	0.3	0.2	0.1	0.2	0.3
	0,8 cap.	0.3	0.2	0.1	0.0	0.1	0.3
I _{max} phase R	1	0.4	0.3	0.2	0.1	0.2	0.4
	0,5 ind.	0.5	0.3	0.2	0.1	0.2	0.4
I _{max} phase S	1	0.1	0.1	0.1	0.1	0.1	0.1
	0,5 ind.	0.1	0.1	0.1	0.1	0.1	0.2
I _{max} phase T	1	0.4	0.3	0.2	0.1	0.2	0.3
	0,5 ind.	0.4	0.3	0.2	0.1	0.2	0.3